Features and Benefits


Better than +/-0.1PPM from -25°C to +70°C 20MHz CMOS output 3.3V supply, 6.0mA maximum current


Typical Applications

Mobile SATCOM Mobile Radio Hand-carry Instrument Femto-cell

Mechanical Drawing & Pin Connections


Drawing No: MD140051-2






Pin	Function					
#1	GND/NC					
#2	GND					
#3	Output					
#4	Supply Voltage					

[Bottom View]



Recommended soldering pattern



Specifications

Oscillator Specification	Sum	Sym Condition	Value			Unit	Note
	Sylli		Min.	Тур.	Max.	Offit	Note
Nominal Frequency	F _{nom}			20.000000		MHz	
Output Wave Form				CMOS			
Output Voltage Level High			2.97			V	
Output Voltage Level Low					0.33	V	
Output Load Capacitance		Operating range			15	pF	
Duty Cycle		Measured at 50% V _{DD} trigger level	45	50	55	%	
Rise and Fall Times		CMOS logic output at 10% to 90%			6.0	ns	
Start Time		•			2.0	ms	
Power Supply							
Supply Voltage	V_{cc}		3.135	3.3	3.465	V	
Supply Current		At maximum supply voltage			6.0	mA	
Frequency Stability		11 7			•		
VS. Temperature		From -25°C to +70°C Ref. to the midpoint between minimum and maximum frequency value			+/-0.1	ppm	
Tolerance at +25°C		Frequency at +25°C, 1hour after 2 times reflow			+/-2.0	ppm	
VS. Supply Voltage		+/-5% change at 25°C			+/-0.3	ppm	
VS. Load Change		+/-10% change at 25°C			+/-0.2	ppm	
Year Aging		First year at 25°C			+/-1.0	ppm	
Phase Noise (typ.)		@10 Hz @100 Hz @1 KHz @10 KHz @100 KHz		-93 -118 -138 -152 -155		dBc/Hz	
				- 10 111			
Parameter		Reference Std.		Test Condition			
Operating Temperature range		-25°C to +70°C					
Storage Temperature range		0 +125°C					
Vibration Test	MIL-STD-883 2007 Condition A JESD22-B103 Condition 1			10 – 2000Hz, 1.52mm, 20g, each axis 4hrs			
Thermal Shock	MIL-STD-883 1010 Condition B JESD22-A104 Condition B			-55°C, 125°C; soak time is 10mins, with total 200 cycles.			
Mechanical Shock	MIL-STD-883 2002 Condition B JESD22-B104 Condition B			1500G, half-sine, 0.5ms, each axis for 3 times			